

# LED TUBES (2835)

(Constant-voltage: AC100-240V)

Made By	Checked by	
ОК	OK	









#### **Features**

- ★ High brightness SMD LED,NO Infrared,UV,Mercury polution.
- ★ 60% Energy saving, compared with conventional fluorescent tube,
- ★ 49999H lifespan, Aluminum with PC construction no potential risk of broken for transportation.
- ★ Solid light source, no potential risk to fade the color for lighting.
- ★ Optical PC diffuser with milk for option, lighting comfortable.
- ★ Warm/pure/cool white all aviable with high CRI
- ★ Quick response, no flicker and dazzle

#### **Photo**






# LED TUBES SPECIFICATIONS


#### Size

Size					
600mm	900mm	1200mm	1500mm		
Power					
9W	14W	18W	25W		
LED Type					
SMD 2835 48pcs	SMD 2835 68pcs	SMD 2835 96pcs	SMD 2835 120pcs		
brightness					
1050LM	1600LM	2100LM	2900LM		
N.W.					
0.17KG	0.28KG	0.3KG	0.46KG		
G.W.					
0.20KG	0.33KG	0.36KG	0.53KG		
Input Voltage	AC100-240V	Color	warm white Natural white		
Base Type	G13 (Rot / \leftarrow le)		Pure white		
Rendering Index	>80	View Angle	160°		
LED'S Operating Life	49, 999Hours	Material	Aluminium+PC		
Operating Temperature	-20°C <b>–</b> +45°C	Storage Temperature	-30°C +65°C		
Certificates	CE TUV ROHS	Color Temperature	2900-3100K 4000-4500K 5500-6000K		


### **Dimensions**




# Light distribution curve



### Rotary G13 Lamp holder use method




1. Put your thumb on the two pins of G13 cap, then outward gently press the rotating part of lamp holder to make the upper end to tilt outward about 2 °(1mm).




 According to the needed angle, adjust the rotating lamp holder or tube to the needed angle.

## LED Tubes installation(Single-ended input)


#### Installation electronic Ballast



#### Installation Inductive Ballast



Package



Product	Root/Box	Product	Root/Box
600mm	100root/Box	1200mm	50root/Box
900mm	50root/Box	1500mm	50root/Box